

USER MANUAL



Training collar for dogs

Packing list

- 1 x transmitter
- 1 X receiver
- 1 X Collar
- 1 X USB cable
- 1 X Test Bulb
- 1X user manual
- contact points (short / long)
- 2 pairs of conductive silicone covers (short / long)
- 1X wrist rope



Functions



*. **Power Button** : Press any button on the remote to activate it.

NOTE: The display will turn off after 1 minute without using the remote control.

1. **Display**: Static discharge, vibration, beep, intensity, battery light indication, lock and channel 1/3 icons will appear on the screen.
2. **Intensity increase button**: Press the button to **increase** the intensity level of static shock, vibration and beep.
3. **Intensity reduction button**: Press the button, you can reduce the intensity level of static shock, vibration and beep.
4. **Lock button**: **Lock and unlock.**
5. **Lighting** : **Three light modes: always on, slow flashing, fast flashing.**
6. **Sound button**: Press the button, the receiver will make a "beep" sound.
7. **Channel 1/3 button**: Press the button to select the dog which *you want to control, between the first dog and the other dogs.*
8. **Vibrate button**: Press the button, the receiver **will start** to vibrate.
9. **Impulse button**: *Press the button, the receiver will discharge.*
10. **USB charging port**: Insert the charging cable into the charging port to charge the remote controller.
11. **USB charging port and rubber cover**: Insert the charging cable into the charger port and charge the receiver.
12. **Contact point**: *Contains a contact point and a conductive silicone cover.*
Note: Conductive silicone cover can also be conductive.
13. **Receiver on/off button**: *Long press the button to turn the receiver on or off.*

Pairing procedure

1. Turning on the transmitter and receiver



2. Press the "power" button again, the red light will come on and you will hear a "beep"



3. Press the "static shock" button on the transmitter and you will hear the "beep" again, indicating that the collar has been paired. Use the test bulb to test the pulse.



4. When the receiver is not working, it will go into sleep mode after 2 minutes. Press any button on the remote control to reactivate it.

How to use two receivers simultaneously:

1. Press the "Channel" button to select the channel 1 you want to pair, then pair it according to the "operation steps".

2. Press the "Channel" button to select the channel 2 you want to pair and follow the "operational steps" to pair.

Note: The pulse level cannot be 0 during the test.

HOW TO USE T504

Note: Charge the product before use! (The limited charging current of the adapter needs less than 1A)

1. Charge the radio:

- 1) Connect the charger cable to the charging port.
- 2) Plug the charger into a standard outlet.
- 3) The battery icon will flash.
- 4) Charge the radio for about one hour for the first charge or until the battery icon stops flashing.

2. Charge the receiver:

- 1) Connect the charger cable to the charging port.
- 2) Plug the charger into a standard outlet.
- 3) The red light on the receiver will flash
- 4) When charging for the first time, charge the receiver for about one hour or until the light on the receiver goes out

3. Pairing the radio and receiver

- 1) Turn on the remote control and press the "Channel" button to select channel 1 for pairing.
- 2) Press the power button on the receiver, the RED light will turn on.
- 3) Press the static shock or vibration or beep button at will, then the receiver collar will emit a "pulse" or "vibration" or "beep".

Note: The green light will flash continuously to indicate that the pairing is successful.

- 4) If the pairing was not successful, repeat steps 3-5.
- 5) To encode the second receiver, press the "Channel" button and select for the second receiver and proceed in the same way.

How to choose the appropriate level for dogs?

Dog size	15-30 LBS	31-50 LBS	51-80 LBS	> 80 LBS
Sound level	1-3	1-3	1-3	1-3
Vibration level	1-5	5-9	9-12	12-16
Impulse level	1-5	3-7	5-9	7-16

Note: When using sound, vibration and impulse mode, select appropriate level according to the size of the dog.

About the product

1. When the transmitter is not in use, the screen will turn off within 1 minute. When the receiver is not in use, it will go into sleep mode in 2 minutes.
2. After the receiver goes into sleep mode, it can be woken up by pressing any button on the transmitter.
3. When the transmitter is locked, it does not respond to any key press.
4. There are 0-3 levels for sound, 0-16 levels for vibration and 0-16 levels for stimulation (when the gear is 0, the receiver will not work). In light mode, it turns off in 2 minutes when no operation. In light mode, it will light up when pressed for the first time. When pressed a second time, it starts flashing slowly. The third press flashes quickly. When you press it a fourth time, it turns off. 5. which can be used for 90 days.

It takes 2 hours to fully charge the receiver, which can be used for about 10 days. It takes 2 hours to fully charge the transmitter,

General dog training tips

The following tips will show you how to get the best performance out of your dog training collar.

1. It is recommended to train one dog at a time.
2. During the first introductory trainings, keep the dog in a familiar outdoor environment. Training in an unfamiliar place can cause the dog to become distracted.
3. Vibrations are more useful for basic obedience training.
4. During training, look for any positive changes in the dog's behavior and don't forget to encourage in time.
5. When putting the collar on, be careful not to pull it too tight around the neck, but make sure it is still tight enough. For optimal function, it is essential to check that the lead is in contact with your dog's skin. If your dog has long fur, you may need to trim the coat slightly to ensure the contact surface adheres well to your dog's skin.
6. It is important to start the collar with the lowest level so as not to shock your dog. You can start by putting the collar on your dog without turning it on, so that he gets used to wearing it and understands that the collar is not meant to disturb him.



Do not use this product on your aggressive dog or if your dog is prone to aggressive behavior. Aggressive dogs can harm people or things around them. If you are unsure whether this product is suitable for your dog, *please consult* your veterinarian or a certified trainer.

Important information

1. To prevent the dog from strangulation when running, moving or shaking, the collar should be tightened so that you can easily insert two fingers under it.
 2. Do not wear the collar for more than 12 hours a day. If possible, reposition the collar every 1 to 2 hours.
 3. Never attach the dog lead to the collar, it will cause excessive pressure on the contact area.
 4. Wash your dog's neck area and collar contact area weekly with a damp cloth.
 5. Check the dog's contact area daily for rash or sores.
- These alerts will help keep your pet safe and comfortable.

FAQ

Q1: How old does my pet have to be before using a training collar?

Answer 1: Your pet should be able to recognize basic obedience commands such as "Sit" or "Stay" This product may be too large for pets under 10 pounds.

Q2: Why is the training collar not working?

Answer 2: First, make sure the transmitter is unlocked, then set the appropriate level of vibration, static shock and beeping based on your dog's characteristics, such as temperament, type, age, weight, etc.

Q3: Can I use the training collar with more than one pet?

A3: Yes, you can easily add one more receiver collar to the system.

Q4: Will I get exactly 600m range with the training collar?

A4: The effective range of the training collar means the direct distance between the remote control and the receiver collar with no obstructions in between. Range may vary depending on terrain, weather, vegetation, battery capacity, and transmission from other radio devices.

Q5: What should I do if my pet's neck becomes red and irritated?

A5: Stop using the product for a few days. If the condition persists for more than 48 hours, seek help from your veterinarian. Check your pet's skin frequently once the skin has recovered.

Q6: How long is the life of a lithium battery?

A6: Our lithium battery can charge 2000 times for remote control and receiver collar.

Q7: How long can my dog wear the receiver collar?

A7: The collar is not intended for permanent wear. We recommend not wearing the collar for more than 12 hours every 24 hours.

Question 8: How long should I train my pet?

Answer 8: Training should be positive and short, about 10-15 minutes is always better.

The device has been approved for use in EU countries and is therefore provided with the **CE mark**. All necessary documentation is available on the website: www.electric-collars.com
Changes to technical parameters, properties and printing errors reserved.

Service center and distribution

Reedog, sro

Sedmidomky 459/8 101

00 Prague 10

Phone: +1 646 980 4569

Email: info@electric-collars.eu