

# **Remote spray dog training device**

[Remote control sprayer for dog training]

## **User Manual**



Thank you for choosing us for your dearest friend, the spray commander with remote control. In order to train most effectively, please read through the manual carefully before using the device and keep the manual properly after reading.

## Safety Notifications



Attention

1. This product is suitable for all sizes of dogs (15lbs to 100lbs).
2. Do not use the device on human beings.
3. Please turn off or remove the device before playing with your dog.
4. Do not have your dog wear it for too long time, ideally less than 8 hours a day.



Warning

1. Never allow children to play the device as a toy
2. Always keep the device and the spray cans away from fire sources and heat (stove, microwave, etc.)
3. Never try to open up/disassemble the device by yourself. The disassemble would cause leakage and break of internal materials and may lead to severe damage. By defective devices please contact us for refund or replacement immediately.
4. Any Misuse other than this manual is not permitted and will not be refunded.

# Product Description



- 1 The "Power" button**  
turn on / off the receiver, and switch to remote-control mode or automatic mode.
- 2 The "Adjust" button**  
set the volume of spray, connect the collar with the remote control, or cancel the current pairing.
- 3 LED 1**  
indicator light
- 4 LED 2**  
indicator light
- 5 Spray nozzle**  
spray mists to train the dog or stop dog's barking.
- 6 Gas-adding hole**  
replenish spray
- 7 Charging port**  
use the USB cable to charge the receiver (charging tools: USB-charger, Charge Pal).
- 8 Audio frequency sensor**  
senses dog's barking and triggers the spray.
- 9 The "CH" button**  
switch the signal channel between receiver A and B.
- 10 11 The "Warning" buttons**  
choose the volume of the warning sound.
- 12 13 The "Spray" buttons**  
choose the volume of the spray.
- 14 Remote-control indicator**  
Pressing the CH button to choose red light channel (for receiver A) or green light channel (for receiver B), with two channels the remote can connect with different receivers and can control them separately

## LED Indicators

There're 2 LED indicators on the collar, which indicate different states of work. For details please refer to the following chart:

State of work	LED1/2	Light	Flashing mode
Turn on/off	LED 1	Green	3 times
Working	LED 1	Green	every 7 seconds
Low power	LED 1	Red	continuously
Charging	LED 1	Red Green	Red light stay lit on while charging, green lights on when fully charged
Pairing	LED 2	Blue	in Pairing
Spray volume	LED 2	Blue Orange	blue for large volume, yellow for small volume
Low spray supply	LED 2	Blue Orange	every 2 seconds



# Operation Instructions



## 1 Setting up

Press and hold the "Power" button for more than 3 seconds until the LED 1 flashes green and you hear "B,B" sound, the device is turned on.



## 2 Try the remote

When the collar is turned on, try the remote with high/low signal sounds and large/medium spray volume.



## 3 Switch to automatic mode

Press the power button quickly for 3 times and LED 2 flashes blue & red. The collar is now in automatic mode.

When the sensor detects barking the collar will spray automatically.



## 4 Spray Control

Press the "Adjust" button to control the spray volume when the device is under automatic mode.

When LED 2 flashes blue light, the device will spray large volume when triggered; when LED 2 flashes orange, the device will spray small volume at triggering.



## 5 Switch back to remote control mode

Press the power button quickly for 3 times and you'll hear "B,B" twice. The collar is now back to remote control.



## 6 Turn off the collar

Press the power button for more than 3 seconds until the LED 1 flashes green for 3 times, the collar is turned off.

## 7 Add another collar

You can add another collar to the remote and control two dogs at the same time. (Collar 1: the original collar; Collar 2: the new collar).



### Step 1: Disconnect Collar 1 with the remote:

Press the "Adjust" button for more than 10 seconds until you hear "B,B" voice (ignoring the flashing of LED 2). Now the remote is disconnected with Collar 1.



### Step 2: Pair Collar 1 with the remote:

①. Press the "Power" button on Collar 1 quickly for 3 times and you will hear "B,B".

②. Press the "CH" button on the remote to choose Channels (Red/Green).

If you want to pair channel Green with Collar 1, press "CH" until LED on the remote is green.

③. Then press and hold the "Adjust" button until the LED 2 flashes blue.

④. Press all signal & spray buttons on the remote, when signals and spray come from Collar 1, the Collar 1 is paired with the remote.

⑤. Wait for more than 30 seconds. Collar 1 is remembering your setting.



### Step 3: Pair Collar 2 with the remote:

①. Press "CH" on the remote to switch to channel Red.

②. Turn on Collar 2. Press the "Power" button on Collar 2 quickly for 3 times and you will hear "B,B".

③. Then press and hold the "Adjust" button until the LED 2 flashes blue.

④. Press all signal & spray buttons on the remote, when signals and spray come from Collar 2, the Collar 2 is paired with the remote.

### Step 4: Try connection

Switch channels and press signal buttons to test the connection.

\*\* use only when you have two Pacasso training collars.

# Features

- **Remote control within 80 meters**

The flexible and compact remote has control range within distance of 80 meters

- **No more accidental spray**

Equipped with barking sensor with highest sensitivity, the collar will not spray out accidentally.

- **100% Waterproof**

The receiver operates normally at rainy days or when your dog is drinking water. (IPX 3 waterproof)

- **Free switch between two modes: remote-control and automatic mode**

The remote control is very convenient for outdoor training if you want your dog to get rid of misbehavior and follow master's command.

The automatic mode can be switched on for indoor use and spray automatically to stop barking.

- **Applicable for 2 dog collars**

the remote can control 2 collars and can be switched between dog A and B.

- **Warning sound**

Use different warning signals to warn the dog's misbehavior while training your dog.

- **Fresh spray and convenient refill**

Spray liquid: the spray is total CFC free and contains natural essential oil. It is an accredited environmentally-friendly product and safe for human and dog.

Large capacity: the collar has larger capacity than any other products in the market. One time filling can be sprayed 44 times and one bottle of spay can supply full filling of 12 times.


- **Rechargeable**

The collar has built-in lithium battery which can be recharged for more than 1000 times.

# User Tips

## Charging & storing

1. If the receiver receives no remote-control signal for 5 minutes, it will automatically enter sleeping mode. To restart it, just hold either the spray button or warning button on the remote for 3 seconds.
2. If not in use for a long time, please store the device with full electricity.



### Refilling the spray

The LED 2 will flash blue continuously when the spray volume is low and needs to be supplied.

Turn off the device before replenishing the liquid. The collar can firstly be turned on after replenishing. Align the aeration tank to the device, with the spray pin horizontally fixed, and press the aeration tank into the gas-adding hole (near the spray nozzle) for 10 seconds.



### Wear the collar on

Correct wearing is the very important for effective use.

Put the collar on and make sure one finger can be put in between the collar and the dog's neck, then adjust the spray nozzle to the center (directly under the dog's nose), and the collar is right in place. You can remove (cut down or burn) the remaining part of the collar band.



Attention: If your dog has long hair, it is necessary to trim the hair before using, to ensure the mist can be sprayed in an effective range.



## Training tips

- 1 If the device is properly installed and used, the training will take effect shortly after several sessions, with no need of long-time training.
- 2 When properly used, the device would warn the dog with instant spray when the dog barks, and after being warned, the dog's attention will be distracted and he will stop barking. After several sessions, the dog will remember the warnings of the device and bark less with self-conscious. Some dogs would show excitement or irritability when wearing the device, they feel confused or unsure about the spray warnings. At this time, the owner is



required to gently guide and comfort your dog, giving him positive feedbacks to guide him to adapt to the warnings. After a while the dog will get used to this training method.

- 3 The collar weighs only 4.52oz (128g), suitable for large, medium and small dogs.
- 4 Long-time use of the device can cause small injuries like bed sores or skin ulcer. To avoid your dog getting hurt, please follow these methods:
  - Check regularly if there is any skin rash or swell on the neck of the dog. Observe your dog in the first one or two days of using.
  - Check the dog regularly to prevent excessive pressure, adjust the collar to make sure a finger can be allowed between the dog's neck and the collar.
  - Clean around the sensor of the device every week. Do not attempt to remove or replace any parts of the product by yourself, which will cause the warranty invalid.
  - If your dog preforms extreme resistance or dangerous reaction toward the device, even under your guidance, please stop using this product immediately.
  - We recommend using this product on dogs older than six months and weighing more than 8 pounds.
  - The training device should not be continuously used for 12 hours within a day.

## FAQ

### ● **Q: I have 2 dogs, can I add another more receiver to this device?**

A: Yes, the remote-control transmitter has 2 signal channels. You can use the red light channel and the green light channel to control 2 dogs separately.

### ● **Q: How far distance can this device remotely control?**

A: It covers a distance of 80 meters in the absence of any interference and ruthless obstacles, but in our use, the terrain, climate, base stations, magnetic fields, obstacles, other radio devices, the strength of its own battery and other factors will affect the effective distance of the remote control.

### ● **Q: How long is the life time of lithium battery of the device?**

A: Our lithium battery can be recharged 1000 times.

● **Q: How long is the strap of the collar?**

A: The total length of the collar is 80cm. It can be adjusted by a belt buckle according to the size of the dog.

● **Q: The dog training device does not work, or the dog does not respond to the signal sent. How should we solve the problem?**

A: Please check whether the remote-controller and the receiver have power. Please also check the selected mode, confirm whether it is in automatic mode or remote-control mode.

## Specifications

**Charger:** USB charger for mobile phone or Charge Pal

**Lithium battery:** DC3.7V

**Working power:** DC3.1V-4.2V

**Standby current:** 240uA

**Spray current:** 10-25mA

**Remote-controller battery:** Model 12V 27A

