

(:15

(5) (3) (8)

QUICK

USER

CARD

**Power On:** Press the **(b)** button to turn on the devices.

)))



16

2

**Dog Selection:** Press the dog channel switch button to cycle among 1–2–3 channels.



🔄 🚯 🚱

**BEEP Training:** Press the BEEP button, the receiver emits 2 beeps. Long press the beep button to execute the instruction without interruption.

4

Vibration Training: Press the vibration button, the receiver starts to vibrate. Long press the vibration button to execute the instruction without interruption.

**E-Shock Training:** Press the E-Shock button and the receiver will release the electric shock. Intensity 0 means the E-Shock is off. The E-Shock does not support uninterrupted execution. Long press is invalid. You must press it every time.











## **PAIRING OPERATION**

Tips: In the 1-pair package, the receiver and controller are already paired on channel 1 by default.

**Operate The Receiver:** In the shutdown state, press and hold the power button for 5 seconds to enter the pairing state, with the red and green lights flashing alternately. At this time, release button and the receiver is waiting for the pairing signal.



2

**Operate The Remote:** First select the desired remote control dog channel, after the receiver is ready for pairing, press and hold the remote control V key for 3 seconds, the remote control will transmit a pairing signal.



2

Automatic Pairing: When the receiver receives the pairing signal, the red and green lights stop flashing alternately, and 3 beeps sound, indicating that the pairing is successful. At the same time, the remote control channel number will also flash for 3 seconds, indicating that the pairing is successful.

**Change The Channel:** If you want to change the receiver's channel, please repeat the above operation.

